Heritage Brass

# Vintage Range - Matt Bronze

## 2G 13A Socket with USB-C+C - 2C-X09.7508.BK




| | |
|---|---|
| **Range** | Vintage Range |
| **Product** | Vintage Range Matt Bronze Switches & Sockets, X09 |
| **Insert Type** | 2G 13A Socket with USB-C+C |
| **Plate Finish** | Matt Bronze |
| **Switch Colour** | Black |
| **Body and Switch Trim** | |
| **Height** | 88 mm |
| **Width** | 148 mm |
| **Fixing Hole Centres** | Box Fixing = 120.6 mm |
| **Minimum Box Depth** | 35 |
| **Current** | 13 Amp |
| **Voltage** | 230 V |
| **Power** | - |
| **Terminal Capacity** | 4 mm2 |
| **Earth Terminal Capacity** | 5 mm2 |
| **Product Class 1** | Face plate must be earthed |
| **Ambient Operating Temperature** | -5Â°C - 40Â°C |
| **Recommended Location** | Indoor use only |
| **Standard** | BS 1363 |

| | | |
|---|---|---|
| All products listed conform to current British or European standards and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN 9001:2008 Quality System. | It is the policy of the company to continually improve products as part of our development program. Therefore, we respect the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are produced within the limitations of reproductions and printing processes are not binding. | Due to manufacturing process we cannot guarantee an exact colour match and shadings of certain finishes. | Correct as 09.11.2026. E&OE |

**British Standards**
The Heritage Brass Electrical Collection is designed and manufactured to comply with the requirements of the relevant British Standards.

M Marcus Ltd.
Telephone: +44 (0)1384247845
Fax 01384 243 312
Email: electsales@m-marcus.com
Website: www.m-marcus.com