

Vintage Range - Matt Bronze

20A Double Pole Switch with Neon - X09.106.BK



| Range | Vintage Range | |
|-------------------------------|---|--|
| | Vintage Range Matt Bronze Switches & Sockets, X09 | |
| | 20A Double Pole Switch with Neon | |
| | Matt Bronze | |
| Switch Colour | Black | |
| Body and Switch Trim | Black | |
| Height | 88 mm | |
| Width | 88 mm | |
| Fixing Hole Centres | Box Fixing = 60.3 mm | |
| Minimum Box Depth | - | |
| Current | 20 Amp | |
| Voltage | 230 V | |
| Power | | |
| Terminal Capacity | 4 mm2 | |
| Earth Terminal Capacity | 5 mm2 | |
| Product Class 1 | Face plate must be earthed | |
| Ambient Operating Temperature | -5°C - 40°C | |
| Recommended Location | Indoor use only | |
| Standard | BS EN 60669-1 | |

| All products listed conform to current British or European standards and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN 9001:2008 Quality System. | It is the policy of the company to continually improve products as part of our development program. Therefore, we respect the right to alter designs and dimensions without prior notice. |
|---|--|--|
| Illustrations and diagrams are produced within the limitations of reproductions and printing processes are not binding. | Due to manufacturing process we cannot guarantee an exact colour match and shadings of certain finishes. | Correct as 17.08.2025. E&OE |



British Standards The Heritage Brass Electrical Collection is designed and manufactured to comply with the requirements of the relevant British Standards.



M. Marcus Ltd. Telephone: +44 (0)1384 247 845 Fax 01384 243 312 Email: electsales@m-marcus.com m.marcus Website: www.m-marcus.com