

# Heritage Brass

## Vintage Range - Antique Brass

Switched Spur with Neon + Cord (13 Amp) - X91.138.BK



<b>Range</b>	Vintage Range
<b>Product</b>	Vintage Range Antique Brass Switches & Sockets, X91
<b>Insert Type</b>	Switched Spur with Neon + Cord (13 Amp)
<b>Plate Finish</b>	Antique Brass
<b>Switch Colour</b>	Black
<b>Body and Switch Trim</b>	Black
<b>Height</b>	88 mm
<b>Width</b>	88 mm
<b>Fixing Hole Centres</b>	Box Fixing = 60.3 mm
<b>Minimum Box Depth</b>	35
<b>Current</b>	13 Amp
<b>Voltage</b>	230 V
<b>Power</b>	-
<b>Terminal Capacity</b>	4 mm <sup>2</sup>
<b>Earth Terminal Capacity</b>	5 mm <sup>2</sup>
<b>Product Class 1</b>	Face plate must be earthed
<b>Ambient Operating Temperature</b>	-5°C - 40°C
<b>Recommended Location</b>	Indoor use only
<b>Standard</b>	BS 1363

All products listed conform to current British or European standards and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN 9001:2008 Quality System.	It is the policy of the company to continually improve products as part of our development program. Therefore, we respect the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are produced within the limitations of reproductions and printing processes are not binding.	Due to manufacturing process we cannot guarantee an exact colour match and shadings of certain finishes.	Correct as 31.08.2025. E&OE



**British Standards**  
The Heritage Brass Electrical Collection is designed and manufactured to comply with the requirements of the relevant British Standards.



M. Marcus Ltd.  
Telephone: +44 (0)1384 247 845  
Fax: 01384 243 312  
Email: [electsales@m-marcus.com](mailto:electsales@m-marcus.com)  
Website: [www.m-marcus.com](http://www.m-marcus.com)