
Heritage Brass

Vintage Range - Rustic Copper (Project Finish)

20A Double Pole Switch with Neon - XRC.106.BK



Range	Vintage Range
Product	Vintage Range Rustic Copper Switches & Sockets, XRC
Insert Type	20A Double Pole Switch with Neon
Plate Finish	Rustic Copper (Project Finish)
Switch Colour	Black
Body and Switch Trim	Black
Height	88 mm
Width	88 mm
Fixing Hole Centres	Box Fixing = 60.3 mm
Minimum Box Depth	35
Current	20 Amp
Voltage	230 V
Power	-
Terminal Capacity	4 mm2
Earth Terminal Capacity	5 mm2
Product Class 1	Face plate must be earthed
Ambient Operating Temperature	-5°C - 40°C
Recommended Location	Indoor use only
Standard	BS EN 60669-1

All products listed conform to current British or European standards and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN 9001:2008 Quality System.	It is the policy of the company to continually improve products as part of our development program. Therefore, we respect the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are produced within the limitations of reproductions and printing processes are not binding.	Due to manufacturing process we cannot guarantee an exact colour match and shadings of certain finishes.	Correct as 11.11.2026. E&OE

British Standards
The Heritage Brass Electrical Collection is designed and manufactured to comply with the requirements of the relevant British Standards.

M. Marcus Ltd.
Telephone: +44 (0)1384247845
Fax: 01384 243 312
Email: electsales@m-marcus.com
Website: www.m-marcus.com